

HD-DS108



Product Features :

- ≥ 10 inches touch screen with resolution of 1920x1200
- ≥ Support 8 channel camera for backup and recharge.
- ≥ Android system supported.
- ≥ Support 1GB Ethernet port for data uploading.
- ≥ Fast data export and battery recharge.
- ≥ Support upload data to the center FTP server automatically, no need local buffer.
- ≥ Support alarm reminding for network error.
- ≥ Support RAID0. RAID1 backup storage.
- ≥ Support local search and playback.



Specifications :

HARDWARE

Smart Code	Supported
Screen	10 inch touch screen, resolution 1920x1200
Memory	2G
Local Storage	Support 2 disks (2TB~8TB optional)
Data interface	8 channel docking slot or USB connection
OS	Android 5.1

SOFTWARE

Software	Multi-cell docking software
----------	-----------------------------

ENVIRONMENT

Working temperature	-20°C-55°C
Working time	7x24 hours continue working

STRUCTURE

Dimension	295mmx400mmx213mm
Weight	14kg
Working power	Normal voltage: AC100V—240V~50/60HZ
Network	One RJ45, 100/1000M
USB	4 USB 2.0 ports

SOFTWARE FUNCTION

Automatically backup	When BWC connect to the terminal, it will back up all the video, audio, pictures and log file automatically.
Storage empty	The terminal will empty all the data in the BWC when the backup finished.



An ISO 9001:2008 Certified Company

Status display

During the backup progressing, it can display the device id, name, group, storage space, backup status and so on.

Upload

All the video files will upload to the center server automatically or manually.

System log

System will record all operation log of the terminal.

Backup time

8 channel 16G data can be finished in 60 minutes, average speed is 4~6MB/S.

Recharging

8 channels BWC can finish recharging in 4 hours and 45 minutes if the unit is OFF, if it's ON, it need about 5 hours.



An ISO 9001:2008 Certified Company